



TAD – ECC83-WB High Performance Dual High-Mu Triode

The TAD[™] ECC83-WB (part number: RT093) is a miniature, high-mu twin triode, selected and recommended for preamp stages of audio frequency amplifiers. The TAD[™] ECC83-WB provides a stunning full tone, present midrange, and distinct natural overtone harmonics.

Perfect for clean or moderate gain preamps as well as for high-gain amps from V2 position and cathode followers because of its high cathode-heater voltage.

For V1 in general but especially for high-gain amps or phono/audio-amps, we recommend the Highgrade version of the TAD[™] ECC83-WB which is the TAD[™] 7025-WB (part number: RT093-HG)

The TAD™ ECC83-WB can replace any 7025, 12AX7WA, 12AX7WB, 12AX7LPS, 12AX7EH, ECC83 or E83CC.

Any

57.0 mm

49.7 mm

22.5 mm

14 g

300 V

-55 V

1.0 W

135°C

<u>10 mA</u> 2.2MΩ

1MΩ

0 V

conventional

E9-1, Small Button 9 Pin

Characteristics of a bogey tube:

Electrical

Mechanical

Height Seated height

Cooling

Diameter

Base

Operating Position

Dimensions (max.)

Approximate net weight

AF Power Amplifier

Positive DC Grid Voltage Negative DC Grid Voltage

Maximum ratings DC plate voltage

Plate dissipation

Cathode Current


Rg-k, self bias max.

Rg-k, fixed bias max


***Without external shielding, nominal values

Bulb temperature (surface hottest point)


Heater:	series	parallel
Voltage (AC or DC)	12.6V +/-0.6	6.3+/-0.3
Current ca.	0.18	0.35
Heating		Indirect
Cathode-to-heater potential, max.		200 V
Direct interelectrode capacitances, max.***		
Grid to plate		1.5 pF
Grid to cathode and heater		1,6 pF
Plate to cathode		0.5 pF
Cathode to heater		5.2nF
Grid reverse current		<0.2uA
Transconductance (nominal)		1.7mA/V
Amplification factor (nominal)		94



Outline View:



Bottom View Noval Base Connections





WWW.TUBEAMPDOCTOR.COM